

Annexure 1 – DR Connection parameters of BOLT Plus Trading system for Equity segment

Trading members can connect to the DR site of BOLT Plus trading system using either BOLT TWS

or 3rd party trading application of empanelled vendors or in-house developed systems through ETI APIs as follows –

1. BOLT TWS Users

Trading members shall have to change the technical connection parameters in the configuration

settings window at the time of login. Configuration settings window can be invoked using the scrip profile icon or “Shift+F12” shortcut keys on BOLT TWS.

Configuration Settings ✕

Connectivity Mode

Production ▼

Interactive Leased Line Internet
 Broadcast Leased Line Internet Direct ▼
 Masters Leased Line Internet

IP Settings (View / Edit)

Leased Line Internet

Segment	Production	Disaster Recovery
	IP	IP
Eq		
IP 1	10 . 255 . 255 . 6	12908
IP 2	10 . 255 . 255 . 7	12908
Eq MCast IP	227 . 0 . 0 . 21	12996
		Mcast IP/Port Same as Production
Derv		
IP 1	10 . 255 . 255 . 46	15908
IP 2	10 . 255 . 255 . 47	15908
Derv MCast IP	228 . 0 . 0 . 1	15901
		Mcast IP/Port Same as Production
Comm/EGR		
IP 1	10 . 255 . 255 . 12	14908
IP 2	10 . 255 . 255 . 13	14908
MCastIP	229 . 0 . 0 . 65	14965
		Mcast IP/Port Same as Production
Currency		
IP 1	10 . 255 . 255 . 13	10908
IP 2	10 . 255 . 255 . 12	10908
MCastIP	229 . 0 . 0 . 21	10996
		Mcast IP/Port Same as Production

Extranet IP 10 . 1 . 101 . 108 10 . 1 . 101 . 213

General Settings

IML Port 6002

Admin Trade CSV File /Feed Format with Deal Code Broadcast Logging

Other Settings

Market Report 6 x 10 Sec

Market Information Update Frequency Medium ▼

Scrip Id / Name Display

Equity ● Derivative ●

2. 3rd party trading application through ETI APIs

i. Connecting through ETI – members shall have to change the technical connection parameters in their respective trading application as follows –

Primary DR – IP: 10.255.241.10; Port: 12908

Secondary DR – IP: 10.255.241.11; Port: 12908

****End of Document****